



1218 Elektronik Kasa Serisi 1218 Elektronic Safe Series

| Model <i>Model</i> | Özellik <i>Features</i> | Dış Ebatlar <i>Outer Dimensions</i> | İç Ebatlar <i>Inner Dimensions</i> | Ağırlık <i>Weight</i> |
|-----------------------|---------------------------------|--|---------------------------------------|--------------------------|
| DR1218-L15V | 15" Laptop Ebat Elektronik Kasa | 225 x 400 x 440 mm | 192 x 396 x 375 mm | 14 Kg |
| DR1218-L15H | 15" Laptop Ebat Elektronik Kasa | 225 x 450 x 370 mm | 192 x 446 x 310 mm | 14 Kg |
| DR1218-L17 | 17" Laptop Ebat Elektronik Kasa | 225 x 400 x 475 mm | 192 x 396 x 410 mm | 16 Kg |

Özellikler

3-6 Haneli kullanıcı şifresi,
6 haneli master kod ile açma imkânı.
Pil bittiğinde, acil açma aparatı (CEU) veya mekanik pas anahtarı ile dışarıdan müdahale ederek açabilme imkanı.
Pil seviyesini, tarihi ve saati dijital ekranda görebilme.
4 Hatalı işlemde sonra 15 dk. kendini bloke etme
Ceza süresini 15, 30, 45, 60 dakika olarak ayarlama imkanı.
Servo motor sayesinde düşük pil tüketimi.
4 adet 1.5 V orta boy alkalin pil ile çalışır.
Bilgisayar destekli kasayı kiraya verebilme imkanı(Oteller için),
Son 1000 açma operasyonunun dökümü
Laptop ebatında kasa içine konulan priz ve kablo bağlantısı(Opsiyonel)
Kasa içinde hareket sensörlü aydınlatma sistemi halı kaplı zemin
Uzun ömürlü ve dayanıklı elektrostatik toz boya ve renk seçenekleri.
Gizli menteşe sistemi.
Nikel kaplı bolt sistemi.
Güçlü dübellere ile kasa içinden montaj imkânı.

Features

Locking and unlocking with 3-6 digit customer code
Possibility of opening the safe with 6 digits master code.
When the batteries run out, possible to open the safe with emergency unit (CEU) or with mechanical passkey from the outside.
Digital to see battery level, date and time.
15 min. self-blocking after 4 wrong operation. (fine mode can be disabled)
Fine mode can be adjusted as 15,30,45 and 60 minutes.
Low battery consumption with servo motor.
Works with 4 x 1,5 V alkaline battery.
Possibility of hiring out the safe which is computer supported.(for hotels)
The last 1000 on operation can be printed out (process, time, date, password)
Optional plug and cable connection inside the safe
Motion-sensor lighting system is available inside the safe carpeted floor
Electrostatic powder paint with different color options.
Hidden hinge system.
Nickel covered bolt system
Possibility of mounting inside the safe with the strong screws